

Technical Parameter

The voltage transformer is in accordance with GB1207 and IEC186 standards...



Type	Rated frequency (Hz)	Voltage ratio (V)	Accuracy class	Rated output (VA)	Ultimate output (VA)	Rated insulation level(kV)
JDZX8-3	50	$\frac{3000}{\sqrt{3}} / \frac{100}{\sqrt{3}} / \frac{100}{\sqrt{3}}$	0.2/6P 0.5/6P	30/100 50/100	500	3.6/24/40
JDZX8-6	50	$\frac{6000}{\sqrt{3}} / \frac{100}{\sqrt{3}} / \frac{100}{\sqrt{3}}$	0.2/6P 0.5/6P	30/100 50/100	500	7.2/32/60
JDZX8-10	50	$\frac{10000}{\sqrt{3}} / \frac{100}{\sqrt{3}} / \frac{100}{\sqrt{3}}$	0.2/6P 0.5/6P	30/100 50/100	500	12/42/75

Note: If user's data go beyond the above-mentioned scope, they may be subjected to an agreement between manufacturer and purchaser. Rated put and its relative accuracy class are alternative.

Outline and Installation Dimension

